



***For Your Convenience: This File Is
Shared By Diesel Parts Direct***



YOUR ONE STOP SUPERSTORE FOR DIESEL ENGINE PARTS

SHOP NOW



PXT-K Series

Pressure Transmitters

Installation Instructions

00-02-0840
2012-06-01
Section 05

Warranty - A limited warranty on materials and workmanship is given with this FW Murphy product.
A copy of the warranty may be viewed or printed by going to <http://www.fwmurphy.com/warranty>



This Murphy instrument is susceptible to damage when exposed to static electrical changes. To avoid this damage, observe the following:

- Disconnect all electrical power to the machine.
- Follow the lock out/tag out safety procedures of your company. Ensure the machine cannot operate during installation.
- Follow the safety warning of the machine manufacturer.
- Read and follow all installation instructions.

In order to consistently bring you the highest quality, full featured products, we reserve the right to change our specifications and designs at any time. The latest version of this manual can be found at www.fwmurphy.com.

Table of Contents

Introduction 1

Applicable Standards 2

Installation Warnings..... 2

Noise..... 3

Mounting 3

PXT-K & PXT Cable Color Identification 4

PXT-K Series Physical Dimensions 5

PXT-K Installation Drawing 6

Specifications..... 7

Model Number Matrix..... 8

(THIS PAGE INTENTIONALLY LEFT BLANK)

Introduction

The PXT-K Series pressure transmitters are state-of-the-art instruments providing 4-20 mA outputs. Each pressure transmitter contains a transducer comprised of a piezoresistive silicon chip mounted on a glass-metal feed-through header welded into a stainless steel housing and filled with silicone oil; the very thin laser-welded stainless steel isolation-diaphragm completes the front side. Media pressure is transferred from the stainless steel isolation-diaphragm, via the oil inside the cell, to the silicon-measuring chip. This construction, combined with the advanced internal signal conditioning circuitry, results in a rugged instrument with extremely small temperature error and class-leading EMI/RFI resistance.

Applicable Standards

US (NEC 500) - Class I, Division 1, 2, Groups A, B, C, D, E, F, G, T6

NACE MR0175 - Compliant with the requirements

Installation Warnings

Pulsating pressure variations such as caused by liquid or gasses under pressure can destroy any pressure transmitter and should be avoided. To avoid damaging surges and hammers, apply pressure slowly and open/close valves gradually.

To avoid damage from pressure hammer and surges, install a surge chamber or a pressure snubber. One such family of products is the Murphy PD-8100 Series pulsation dampener. Contact Murphy for details or check on www.fwmurphy.com/.

Symptoms of fluid hammer and surge damage:


- a. Pressure transmitter exhibits an output at zero pressure (large zero offset).
- b. Pressure transmitter output remains constant regardless of pressure.
- c. In severe cases, there will be no output.

Noise

For minimum noise susceptibility avoid running the transmitter cabling in a conduit that contains high voltage AC power cables or the ignition loom on an engine. Where possible avoid running the cable near inductive equipment. Shielded cable is always recommended. Typical shield/drain is isolated from the transmitter body and should be grounded on the panel end only. **However, PXT-K Series products are not constructed to be isolated and the shield/drain should not be grounded in the panel.**

Mounting

Caution: Transmitters are precision instruments. Do not install in a manner that causes side stress or is subject to excessive vibration.



Transmitters require no special mounting hardware and can be mounted in any plane with negligible position error.



Although the unit can withstand substantial vibration without damage or significant output effects, it is good practice to mount the transmitter where there is minimum vibration.

Apply Teflon tape/sealant to the pressure-fitting threads before installing. When tightening, apply a wrench to the hex wrench flats located just above the pressure fitting. **DO NOT tighten by using a pipe wrench on the housing.**

PXT-K and PXT Series Pressure Transmitter Cabling Identification


The PXT Series Pressure Transmitters have changed. Previous pressure transmitters in this series were identified as ***PXT Pressure Transmitters***. The newest version is the ***PXT-K Series Pressure Transmitters***. Identification of electrical cable color is NOT interchangeable between the two series of pressure transmitters.

The following information will assist you in identifying the pressure transmitter unit you have and the correct electrical cable colors to avoid wiring mistakes.

PXT SERIES	PXT-K SERIES
 <p>Indentations on the hex coupling for controlled locking.</p> <p>Product has a step-down between the transmitter body and hex coupling.</p>	 <p>No step-down between the body and the hex coupling.</p> <p>No indentations on the hex coupling.</p>

Cable Color	Connection	Cable Color	Connection
RED	POWER	RED	POWER
BLUE	SIGNAL	BLUE	N/A
BLACK	CASE GROUND	BLACK	SIGNAL
ORANGE, YELLOW, WHITE	N/A	ORANGE, YELLOW, WHITE	N/A
Installation Instructions	00-02-0475	Installation Manual	00-02-0840
Installation Diagram	05-08-0754	Installation Diagram	05-08-0763

PXT-K Series Physical Dimensions



Specifications

Operating Pressure Range: See the part number matrix following this section.

Operating Temperature: -40 to 180°F (-40 to 82°C).

Compensated Temperature Range: -20 to 160°F (-29 to 71°C).

Physical Characteristics:

Process Connection: 1/4 NPT female with 7/8" Hex Nut.

Electrical Connection (PXT-K-XXX): 1/2" NPT Male Conduit connection with 60" long cable, vented

Enclosure: NEMA 4/IP65 or better

Body: 316L Stainless Steel. Meets NACE MR01-75.

Wetted Parts: 316L stainless steel

Environmental Effect (Humidity): No effect for 0-95%, Non-condensing

Mounting: Transmitter can be installed in any axis. Transmitter position has negligible effect on performance as long as it is perpendicular to the flow being monitored.

Shock Resistance: 1000g per IEC 60068-2-6 (Mechanical Shock)

Vibration Resistance: 20G per IEC 60068-2-6 (Vibration under resonance)

Wiring Protection: Protected against reverse polarity and short circuit, 48 VDC Maximum

Supply Voltage: 8 - 30 VDC (Typically 24 VDC)

Insulation: Greater than 10MΩ @ 300 VDC

Electromagnetic Compatibility (EMC): Standards; EN 61000-6-2:2005, EN 61000-6-3:2007, EN 61326-2-3:2006

Voltage Surge/Spike Protection: Protection against a 600 Volt spike per IEC 60-2

Murphy two wire pressure transmitter with flying lead connection, 0-600 psig range, 4-20 mAdc output. If no digit follows Pressure Range, it is automatically a 4-20 mAdc output signal.

